

(12) **UK Patent Application** (19) **GB** (11) **2 341 933** (13) **A**

(43) Date of A Publication 29.03.2000

<p>(21) Application No 9921925.5</p> <p>(22) Date of Filing 17.09.1999</p> <p>(30) Priority Data (31) 9820910 (32) 26.09.1998 (33) GB</p>	<p>(51) INT CL<sup>7</sup> G06K 11/12 // G01L 1/20</p> <p>(52) UK CL (Edition R) G1N NAQB N1A3B N1D9 N7H2 N7S H1N NBH NUJD N449 N618 N705 N707 N744 N854</p>
<p>(71) Applicant(s) Electrotextiles Company Limited (Incorporated in the United Kingdom) 2 Bloomsbury Street, LONDON, WC1B 3ST, United Kingdom</p> <p>(72) Inventor(s) David Lee Sandbach</p> <p>(74) Agent and/or Address for Service Atkinson Burrington The Technology Park, Shirland Lane, SHEFFIELD, S9 3PA, United Kingdom</p>	<p>(56) Documents Cited GB 1308575 A</p> <p>(58) Field of Search UK CL (Edition R) G1N NACH NACNR NAEPR NAGBR NAGB10 NAGB8 NAQB, H1N NUJD INT CL<sup>7</sup> G01L 1/20, G06K 11/12 ONLINE : WPI, EPDOC, JAPIO</p>

(54) Abstract Title  
**Position detector constructed from conductive fabric**

(57) A position detector comprises at least two planes 1621, 1622 of electrically conductive fabric, at least one of the planes having an electrical characteristic eg resistance which differs significantly in value from that of the first plane. A mechanical interaction on the surface brings opposed planes together and results in an electrical output. One of the planes is used as a detector whilst voltages are applied sequentially in different directions to a co-operating plane. Current flow between planes increases significantly with an increase in the area of mechanical interaction, thereby improving the definition of the detector. A second electrical characteristic may be used to identify additional properties of a mechanical interaction eg applied force, area of contact or orientation of an object. The fabric can be woven (Fig.4), non-woven eg felt or knitted and can combine conductive and insulative fibres. Electrical signals can be derived independently by Time Division Multiplexing TMD (Fig. 3) via a micro-controller (201, Fig.2) operated circuit (121, Fig.2).




Figure 16




Figure 1

2/19




Figure 2

3/19




Figure 3

4/19




Figure 4

5/19







Figure 5

6/19

*Figure 6*

7/19




Figure 7



8/19







Figure 8






Figure 9

10/19

*Figure 10*

11/19




Figure 11A




Figure 11B

12/19




Figure 12A




Figure 12B

13/19




Figure 13

14/19




Figure 14




Figure 15



16/19




Figure 16

17/19




Figure 17

18/19




Figure 18






Figure 19

19/19

*Figure 20**Figure 21*

## Detector Constructed From Fabric

5 The present invention relates to a detector constructed from fabric having electrically conductive elements to define at least two electrically conductive planes.

A fabric touch sensor for providing positional information is described in United States patent 4,659,873 of Gibson. The sensor is fabricated using two layers of fabric having conducting threads, separated by a resistive layer to prevent unintentional contact.

10 An improvement to this known configuration is proposed in the applicant's co-pending British patent application number 98 20 902 in which there is provided a position detector constructed from fabric having electrically conductive elements, comprising at least two electrically conductive planes. A potential is applied across at least one of the planes to determine the position of a mechanical interaction. In addition, a second  
15 electrical property is determined, such as current, to identify additional properties to the mechanical interaction, such as an applied force, an applied pressure or an area of contact.

20 A further proposal is included in the applicant's co-pending British patent application number 98 20 905 in which there is provided a detector constructed from fabric having electrically conductive elements defining at least two electrically conductive planes and configured to produce electrical outputs in response to mechanical interactions. At least one of the planes includes first portions and second portions, wherein the first portions have a  
25 higher resistance than the second portions and the first higher resistance portions are more flexible than the second portions.

30 A third proposal is described in the applicant's co-pending British patent application number 98 20 906, in which there is provided a detector constructed from fabric having electrically conductive elements and configured to produce electrical outputs in response to mechanical

interactions. The detector surface is divided into a plurality of regions and each of these regions includes a first conducting plane and a second conducting plane. A mechanical interaction results in conducting planes of at least one of said regions being brought closer together.

5           A fourth proposal is described in the applicant's co-pending British patent application number 98 20 908 in which there is provided a fabric constructed from a electrically conducting fibres and from electrically insulating fibres by a mechanical process. Electrical connection means are connected to electrically conducting fibres of the fabric during the  
10           mechanical process. Thus, the fourth improvement provides for securely attaching electrical connectors to electrically conducting fibres, thereby reducing the risk of said connectors becoming detached during use of the detector.

          A fifth improvement is disclosed in the applicant's co-pending British  
15           patent application number 98 20 909, in which there is provided a detector constructed from fabric having electrically conductive elements to define at least two electrically conductive planes and configured to produce an electrical output in response to a mechanical interaction, wherein a conductivity non-uniformity is included in at least one of said planes so as to  
20           modify an electrical response to a mechanical interaction.

          According to a first aspect of the present invention, there is provided a detector constructed from fabric having electrically conductive elements to define at least two electrically conductive planes and configured to produce an electrical output in response to a mechanical interaction, wherein a  
25           second electrically conductive plane of said detector has at least one electrical characteristic that differs significantly in value from the value of said characteristic of the first plane.

          In a preferred embodiment, one of the planes is used as a detector and voltages are applied sequentially in different directions to other co-  
30           operating plane. Preferably, the electrical characteristic is electrical

resistance.

According to a second aspect of the present invention, there is provided a method of constructing a detector, comprising the steps of constructing electrically conductive elements from fabric to determine at least  
5 two electrically conducting planes configured to produce electrical output in response to a mechanical interaction; and configuring a second electrically conductive plane of said detector with at least one electrical characteristic that differs significantly in value from the value of said characteristic of said first plane.

10 The invention will be described by way of example only, with reference to the accompanying drawings of which:

Figure 1 shows a position detector constructed from fabric;

Figure 2 shows a control circuit identified in Figure 1;

15 Figure 3 details operations performed by the micro-controller identified in Figure 2;

Figure 4 details planes identified in Figure 1;

Figure 5 details current flow due to mechanical interaction;

Figure 6 details an alternative construction for conducting fabric  
planes;

20 Figure 7 shows an alternative configuration of conducting planes;

Figure 8 shows an alternative configuration of conducting planes;

Figure 9 details a composite configuration of conducting planes; and

Figure 10 shows an asymmetric object interacting with conducting  
planes.

25 Figure 11A and Figure 11B show an alternative construction for a detector;

Figure 12A and Figure 12B show a further alternative construction;

Figure 13 shows a further alternative construction;

Figure 14 shows a further alternative construction.

Figure 15 shows an alternative embodiment having a plurality of detectors;

Figure 16 shows an alternative detector configuration; and

Figure 17 shows multiple detectors of the type shown in Figure 16.

5        Figure 18 shows a first embodiment in which a connector has been included during the machining process; and

Figure 19 shows an alternative embodiment in which a connector has been added during a machining process.

10       Figure 20 shows a detector constructed from fabric having a conductivity non-uniformity; and

Figure 21 shows an alternative embodiment with a conductivity non-uniformity.

15       A position detector 101 constructed from fabric is shown in Figure 1. The detector has two electrically conducting fabric planes, in the form of a first plane 102 and a second plane 103. The planes are separated from each other and thereby electrically insulated from each other, by means of an insulating mesh 104. When force is applied to one of the planes, the two conducting planes are brought together, through the mesh 104, thereby creating a position at which electrical current may conduct between planes 102 and 103. In this way, it is possible to identify the occurrence and/or position of a mechanical interaction.

20       The fabric planes are defined by fabric structures, which may be considered as a woven, non-woven (felted) or knitted etc. The fabric layers may be manufactured separately and then combined to form the detector or the composite may be created as part of the mechanical construction process.

25       When a voltage is applied across terminals 107 and 108, a voltage gradient appears over plane 102. When a mechanical interaction takes place, plane 103 is brought into electrical contact with plane 102 and the actual voltage applied to plane 103 will depend upon the position of the

30



interaction. Similarly when a voltage is applied between connectors 111 and 112, a voltage gradient will appear across plane 103 and mechanical interaction will result in a voltage being applied to plane 102. Similarly, the actual voltage applied to plane 102 will depend upon the actual position of the interaction. In this way, for a particular mechanical interaction, it is possible to identify locations within the plane with reference to the two aforesaid measurements. Thus, connectors 107, 108, 111 and 112 are received by a control circuit 121, configured to apply voltage potentials to the detector 101 and to make measurements of electrical properties in response to mechanical interactions.

Control circuit 121 identifies electrical characteristics of the sensor 101 and in response to these calculations, data relating to the characteristics of the environment are supplied to a data processing system, such as a portable computer 131, via a conventional serial interface 131.

Control circuit 121 is detailed in Figure 2. The control circuit includes a micro-controller 201 such as a Philips 80C51 running at a clock frequency of twenty megahertz. Operations performed by micro-controller 201 are effected in response to internally stored commands held by an internal two kilobyte read-only memory. The micro-controller also includes one hundred and twenty-eight bytes of randomly accessible memory to facilitate intermediate storage while performing calculations. Micro-controller 201 includes a serial interface 202 in addition to assignable pins and an interface for communicating with an analogue to digital converter 203, arranged to convert input voltages into digital signals processable by the micro-controller 201.

The control circuit 121 includes two PNP transistors 211 and 212, in addition to four NPN transistors 213, 214, 215 and 216. All of the transistors are of relatively general purpose construction and control switching operations within the control circuit so as to control the application

of voltages to the position detector 101.

In operation, measurements are made while a voltage is applied across first plane 102 and then additional measurements are made while a voltage is applied across the second plane 103; and output voltage only being applied to one of the planes at any particular time. When an output voltage is applied to one of the planes, plane 102 or plane 103, input signals are received from the co-operating plane 103 or 102 respectively. Input signals are received by the analogue to digital converter 203 via a selection switch 221, implemented as a CMOS switch, in response to a control signal received from pin C6 of the micro-controller 201. Thus, in its orientation shown in Figure 2, switch 221 has been placed in a condition to receive an output from a first high impedance buffer 222, buffering an input signal received from plane 102. Similarly, when switch 221 is placed in its alternative condition, an input is received from a second high impedance buffer 223, configured to receive an input signal from plane 103. By placing buffers 222 and 223 on the input side of CMOS switch 221, the switch is isolated from high voltage electrostatic discharges which may be generated in many conditions where the detector undergoes mechanical interactions.

In the condition shown in Figure 2, switch 221 is placed in its upper condition, receiving input signals from buffer 222, with output signals being supplied to the second plane 103. Further operation will be described with respect to this mode of operation and it should be appreciated that the roles of the transistor circuitry is reversed when switch 221 is placed in its alternative condition. As previously stated, condition selection is determined by an output signal from pin C6 of micro-controller 201. In its present condition the output from pin C6 is low and switch 221 is placed in its alternative configuration when the output from pin 6 is high.

Output pin C0 controls the conductivity of transistor 211 with pins C1 to C5 having similar conductivity control upon transistors 212, 213, 214, 215 and 216 respectively.

Transistors 211 and 213 are switched on when a voltage is being applied to the first plane 102 and are switched off when a voltage is being applied to the second plane 103. Similarly, when a voltage is being applied to the second plane 103, transistors 212 and 215 are switched on with transistors 211 and 213 being switched off. In the configuration shown in Figure 2, with switch 221 receiving an input from buffer 222, output transistors 211 and 213 are switched off with output transistors 212 and 215 being switched on. This is achieved by output pin C0 being placed in a high condition and pin C1 being placed in a low condition. Similarly, pin C3 is placed in a low condition and pin C4 is placed in a high condition.

In the configuration shown, C3 is placed in a low condition, as previously described. The micro-controller 201 includes a pull-down transistor arranged to sink current from the base of transistor 212, resulting in transistor 212 being switched on to saturation. Consequently, transistor 212 appears as having a very low resistance, thereby placing terminal 111 at the supply voltage of five volts. Resistor 231 (4K7) limits the flow of current out of the micro-controller 201, thereby preventing burn-out of the micro-controller's output transistor.

Pin C4 is placed in a high state, resulting in transistor 215 being placed in a conducting condition. A serial resistor is not required given that the micro-controller 201 includes internal pull-up resistors, as distinct from a pull-up transistor, such that current flow is restricted. Thus, transistors 212 and 215 are both rendered conductive, resulting in terminal 111 being placed at the positive supply rail voltage and terminal 112 being placed at ground voltage. The capacitors shown in the circuit, such as capacitor 219, limit the rate of transistor transitions thereby reducing rf transmissions from the sensor 101.

With transistors 212 and 215 placed in their conductive condition, input signals are received from the first plane 102 in the form of a voltage applied to terminal 108. For position detection, this voltage is measured

directly and transistor 214 is placed in a non-conductive condition by output pin C2 being placed in a low condition. Under these conditions, the voltage from input terminal 108 is applied to analogue to digital converter 203 via buffer 222 and switch 221.

5 In accordance with the present invention, a second electrical property is determined which, in this embodiment, represents the current flowing through the sensor in response to a mechanical interaction. The current measurement is made by placing transistor 215 in a conductive condition, by placing output pin C4 in a high condition. In this condition, 10 current received at terminal 108 is supplied to transistor 214 via resistor 214A, having a resistance of typically 5k selectable so as to correspond to the characteristics of the sensor. A voltage is supplied to A to D converter 203 via buffer 222 and switch 221 but on this occasion the voltage represents a voltage drop, and hence a current, across resistor 214A.

15 Thus, transistors 212 and 215 are placed in a conducting condition, transistor 214 is placed in a non-conducting condition, so as to measure voltage, and is then placed in a conducting condition so as to measure current. The roles of the transistors are then reversed, such that output transistors 211 and 213 are placed in a conducting condition, with 20 transistors 212 and 215 being placed in a non-conducting condition (and switch 221 reversed) allowing a voltage to be measured by placing transistor 216 in a non-conducting condition, and then allowing a current to be measured by placing transistor 216 in a conducting condition.

The cycling of line conditions, in order to make the measurements 25 identified previously, is controlled by a clock resident within micro-controller 201. After each condition has been set up, a twelve bit number is received from the digital to analogue converter 203 and this number is retained within a respective register within micro-controller 201. Thus, after completing a cycle of four measurements, four twelve bit values are stored 30 within the micro-controller 201 for interrogation by the processing device

131. Furthermore, the rate of cycling may be controlled in response to instructions received from the processing device 131.

Operations performed by micro-controller 201 are detailed in Figure 3. The micro-controller continually cycles between its four configuration states and each time a new input is produced, representing a current or a voltage in one of the two configurations, new output data is calculated on an on-going basis. Thus, output registers are updated such that the best data is made available if the micro-controller is interrupted by the external processor 131.

The micro-controller 201 is fully interrupt driven in terms of receiving external interrupts for data interrogation along with internal interrupts in order to initiate a configuration cycle. The external interrupt has a higher priority such that external processor 131 is provided with information as soon as possible in response to making an interrupt request.

Internally interrupts for the micro-controller 201 are generated by its own internal timer and the procedure shown in Figure 3 is effectively held in a wait state until a next timer interrupt is received at step 301. The wait state allows voltage levels on connections 107, 108, 111 and 112 to become stable and provides sufficient time for valid data to be received from the analogue to digital converter 203.

At step 302, an output is received from analogue to digital converter 203 and at step 303 calculations are performed with respect to the most current data received from the analogue to digital converter, so as to convert numerical values relating to voltages and currents into numerical values representing properties of the mechanical interaction. Thus, after performing calculations at step 303, appropriate registers are updated at step 304 and it is these registers that are interrogated in response to an interrupt received from processing system 131.

At step 305 next conditions for the output lines are set by appropriate logic levels being established for output pins C0 to C6. After the

next output condition has been selected, the processor enters a wait state at step 306, allowing the electrical characteristics to settle, whereafter processing continues in response to the next timer interrupt.

Thus, it should be appreciated that on each iteration of the procedure shown in Figure 3, one of the output conditions is selected at step 305. Thus, it should be appreciated that the input data is effectively delayed and does not represent a condition of the electrical characteristics at an instant. If in practice, the delay between measurements becomes too large, it becomes necessary to enhance the frequency of operation of circuits within the control system shown in Figure 2. Thus, the rate of conversion for converter 203 would need to be increased and the circuitry would need to be redesigned for high frequency operation. This in turn could create problems in terms of high frequency interference resulting in enhanced shielding being required for the facility as a whole.

When output condition number one is selected, an output voltage at 108 is determined. On the next cycle, identified as output condition number two, the current flowing through connector 108 is determined. On the next iteration, under output configuration number three, the voltage appearing at connector 112 is determined and on the next cycle, identified as condition number four, the current flowing through connector 112 is determined. After each of these individual measurements, new data is generated in response to steps 303 and 304 such that resulting output registers are being regularly updated on a continual basis, such that the processing system 131 may effectively perform a continual monitoring operation in terms of changes made to the mechanical interactions with the detector 101.

In a typical implementation, the four characteristic measurements, making up a complete cycle, will be repeated at a frequency of between twenty-five to fifty times per second. In situations where such a repetition rate is not required, it may be preferable to increase the duration of the wait states and thereby significantly reduce overall power consumption.

Planes 102, 103 and 104 of the detector 101 are detailed in Figure 4. Planes 101 and 103 are of substantially similar construction and are constructed from fabric having electrically conductive elements 402 in plane 102 along with similar electrical conductive elements 403 in plane 103. Thus, it is possible for a voltage indicative of position to be determined when conductive elements 402 are placed in physical contact with conductive elements 403.

The overall resistivity of planes 402 and 403 are controlled by the inclusion of non-conducting elements 404 and 405. Thus, resistivity is controlled by controlling the relative quantities and/or densities of conductive elements 402 with non-conductive elements 404. Resistivity may also be controlled by selecting an appropriate fibre type, adjusting the thickness of the fibre or adjusting the number of strands present in a yarn.

Plane 404 represents a non-conducting insulating spacer positioned between the two conducting planes 102 and 103. Plane 104 is constructed as a moulded or woven nylon sheet having an array of substantially hexagonal holes 411, the size of holes 411 is chosen so as to control the ease with which it is possible to bring conductive elements 402 into physical contact with conductive elements 403. Thus, if relatively small holes 411 are chosen, a greater force is required in order to bring the conductive elements together. Similarly, if the size of the hole is increased, less force is required in order to achieve the conductive effect. Thus, the size of holes 411 would be chosen so as to provide optimal operating conditions for a particular application. Operating conditions may also be adjusted by controlling the thickness of layer 104, its surface flexibility and the contour of co-operating planes 102 and 103.

When a potential is applied across one of the conducting planes, the actual potential detected at a point on that plane will be related to the position at which the measurement is made. Thus, a direct voltage measurement from the co-operating plane gives a value from which a

positional co-ordinate may be determined. By reversing the plurality of the planes and taking a measurement from the opposing plane, two co-ordinates are obtained from which it is then possible to identify a precise location over the planar surface.

5 In addition to measuring position on the planar surface, the present invention is directed at identifying additional electrical properties in order to determine properties of the mechanical interaction. As previously described, the system is configured to measure currents in addition to measuring voltages.

10 When the two conducting planes are brought into mechanical contact, due to a mechanical interaction, the amount of current flowing as a result of this contact will vary in dependence upon the actual position of the plane where the mechanical interaction takes place. The position of the mechanical interaction has also been determined with reference to voltages  
15 and it could be expected that these two quantities will vary in a substantially similar way, each representing the same physical situation. Experience has shown that variations in measured current do not follow exactly the same characteristic as variations in measured voltage. As illustrated in Figure 5, the amount of current flowing due to a mechanical interaction will depend  
20 upon the position of a mechanical interaction 501. However, in addition to this, the amount of current flow will also depend upon the size of the mechanical interaction. As the size of the mechanical interaction increases, there is a greater area of contact and as such the overall resistance of the mechanical interaction is reduced. However, it should be appreciated that  
25 variations in terms of current with respect to interaction size is a sophisticated relationship, given that, in addition to the resistivity of the contact area 501, the resistivity of the actual electrical connections within the sheet must also be taken into account.

30 Thus, current is transmitted through a region 502 in order to provide a current to the contact region 501. Some aspects of this effect will be



compensated with reference to position calculations and other variations due to this effect may be compensated by a non-linear analysis of the input data.

5 Contact area resistivity is illustrated generally at 510 and shows that the amount of current flowing between plane 102 and plane 103 is considered as being related to the area of mechanical interaction, which is related to the area of contact externally and to the level of externally applied mechanical force.

10 The resulting non-linear relationship between the force area product and the resulting current flow is illustrated generally at 520. At 521 there is an initial threshold point, identifying the point at which the gap starts to be closed, followed by an operational part of the curve which may give useful indications of pressure up to point 522, whereafter the relationship becomes very non-linear until position 523 where the relationship effectively  
15 saturates.

Using a detector of the type illustrated in Figure 1, it is possible to measure current flow, which could also be considered as contact resistance, in order to identify an additional mechanical property of the interaction. As illustrated in Figure 5, this other mechanical property is  
20 related to the area of contact between the sheets, determined by the amount of force applied to the sheets, and to the total area over which the force is applied; or a combination of these two properties. Thus, data relating to force and area may give useful information relating to the interaction, separate from the position at which the interaction takes place.

25 In some situations, such as when using a stylus or similar implement, the area of applied force remains substantially constant therefore a measurement of current will enable calculations to be made in terms of stylus pressure. Pressure sensitive styli are known but in known configurations the pressure detection is determined within the stylus itself,  
30 leading to the stylus being mechanically connected to operational

equipment or requiring sophisticated wireless transmission within the stylus itself. The present embodiment allows stylus pressure to be determined using any non-sophisticated stylus, given that the pressure detection is made by the co-operating fabric detector, arranged to detect stylus position (with reference to voltage) in combination with stylus pressure, with reference to current.

An alternative construction for the conducting fabric planes is illustrated in Figure 6. The detector includes a first conducting plane 601 and a second conducting plane 602. In addition, woven into each of the conducting planes 601 and 602, there are a plurality of non-conducting nodes 605 arranged to mutually interfere and thereby separate the two conducting planes. Between the nodes, the fabrics of the first and second planes may be brought into contact relatively easily such that the application of force, illustrated by arrow 611 would tend to cause a finite number of regions interspersed between nodes 605 to be brought into contact. Thus, for a particular region, contact either is taking place or is not taking place as illustrated by curve 621.

With a number of such regions brought into contact, the overall level of current flow will tend to vary with the area of contact as illustrated by curve 631. Thus, using a construction of the type shown in Figure 6, it is possible to obtain a more linear relationship, compared to that shown in Figure 5, in which the level of current flow gives a very good indication of the area of coverage as distinct from the level of force applied to the mechanical interaction.

Given a construction of the type shown in Figure 6, an indication of applied force or pressure may be obtained, in addition to an accurate determination of area, by providing an incremental switching operation. In the configuration shown in Figure 7, there is provided a first conducting plane 701 which interacts with a second conducting plane 702. Furthermore, conducting plane 702 interacts with a third conducting plane

704. Conducting plane 701 is separated from conducting plane 702 by non-conducting portions 705. Similarly, plane 702 is separated from plane 704 by non-conducting portions 706. More non-conducting portions 705 are provided than similar non-conducting portions 706. Consequently, less force is required to produce electrical contact between planes 701 and 702 than is required to produce an electrical contact between planes 702 and 704. In this way, it is possible to provide an incremental measurement of force, given that a low force will only cause contact between plane 701 and plane 702 whereas a larger force will also provide electrical contact between plane 702 and 704.

An alternative configuration is shown in Figure 8 in which it is possible to obtain enhanced substantially continuous variations in current flow with respect to applied force. A first conducting plane 801 interacts with a second conducting plane 802. The planes are woven in such a way as to produce very uneven surfaces such that, under light load, the level of interaction is relatively low. As load increases, as illustrated generally at 805, a greater level of surface contact shown at 806 is created thereby increasing the level of current flow in a substantially continuous way. It should also be noted that this configuration does not include an insulating layer as such and that a level of current flow will always take place even under conditions of zero load. Alternatively, a very thin insulating layer could be provided, having a relatively low threshold, thereby resulting in a zero current flow when no load is applied.

As shown by curve 811, the output current varies with respect to variations in applied force for a constant load area. Similarly, as shown by curve 821, output current varies with respect to load area for a substantially constant applied force.

A composite configuration is shown in Figure 9, in which a detector 901, substantially similar to that shown in Figure 6, is combined with a detector 902, substantially similar to that shown in Figure 9. Detector 901

provides an accurate measurement of applied area and it is relatively unaffected by applied force. Detector 902, as shown in Figure 8, provides an output which varies with respect to area and force. Thus, by processing the output of these two detectors in combination, it is possible to  
5 compensate the output from detector 902 in order to produce values representing force, such that the two currents provide indications of both force and area.

The operation of the control circuit 121 is such as to apply a first voltage across diagonals 107 and 108 with a similar voltage being applied  
10 across diagonals 111 and 112. The nature of the voltage distribution is therefore asymmetric, but this does not result in difficulties provided that the area of contact between the two planes is relatively symmetric. However, should an asymmetric area of contact be made, as illustrated in Figure 10, differences will occur in terms of current measurements when considering  
15 calculations made in the two directions.

An asymmetric object 1001 is shown applied to the surface of a detector 1002. When a voltage is applied between contact 107 and 108, paths over which current may flow, illustrated generally at 1003 are relatively large and the object is perceived as having a large area or is  
20 perceived as applying a large force. In the opposite dimension, when a voltage is applied between 111 and 112, the regions over which current flow takes place illustrated generally at 1105, become relatively smaller therefore the object would be perceived as having a relatively smaller area or would be perceived as providing a relatively smaller force.

25 If the system is programmed to the effect that the object has a constant area and applies a constant force, these differences in terms of current flow may be processed in order to give an indication as to the orientation of the object. Thus, the system of the type illustrated in Figure 10, is used in combination with the detector of the type illustrated in Figure  
30 9 it is possible to make reference to the parameters of location in two-

dimensions, force or pressure, the area of application and orientation.

In the preferred embodiment, electrical characteristics of voltage and current are measured. Alternatively, it would be possible to determine the resistance or the resistivity of the conducting sheets. Problems may be encountered when using alternating currents due to energy being radiated from the conducting sheets. However, in some situations it may be preferable to use alternating currents, in which further electrical characteristics of the detector may be considered, such as capacitance, inductance and reactance etc.

The detector shown in Figure 1, constructed from conducting planes 102 and 103, operates satisfactorily if the plane of the detector is maintained substantially flat. This does not create a problem in many applications where relatively flat operation is considered desirable. However, although constructed from fabric, thereby facilitating bending and folding operations, the reliability of the detector in terms of its electrical characteristics cannot be guaranteed if the detector planes are folded or distorted beyond modest operational conditions.

A detector is shown in Figure 11, constructed from fabric having electrically conductive elements to define at least two electrically conductive planes. The detector is configured to produce an electrical output in response to a mechanical interaction, as illustrated in Figure 1. At least one of the planes includes first portions and second portions in which the first portions have a higher resistance than said second portions and the first higher resistance portions are more flexible than the second portions. In this way, flexing occurs at the portions of high resistance, where contact between the planes has little effect, while the lower resistance portions, where contact does have a strong electrical effect, remain substantially rigid such that the flexing of the material does not occur over these portions of the detector.

Portions 1101 have a relatively high resistance compared to portions 1102. Portions 1101 are not involved in terms of creating an electrical reaction in response to a mechanical interaction. The electrical responses are provided by the more rigid weave of portions 1102. The purpose of portions 1101 is detailed in Figure 11B. A curvature has been applied to the detector but the configuration is such that normal operation is still possible. The flexing has occurred predominantly at portions 1101. However, portions 1102 have remained straight thereby ensuring that they remain displaced from each other, even when a curvature is present, such that the detector is still available for detecting the presence of a mechanical interaction.

The rigidity of portions 1102 may be enhanced as shown in Figure 12A. A first plane 1201 has rigid portions 1202 and flexible portions 1203. A second plane 1204 has relatively rigid portions 1205 and relatively flexible portions 1206. The relatively flexible portions 1206 physically contact against similar portions 1203 in the first plane 1201. In order to ensure that there is no, or at least minimal electrical interaction at these points of contacts, the electrical resistance of the flexible portions 1203 and 1206 is relatively high. A partially insulating layer may be provided between the conducting layers, as shown in Figure 1. However, the flexible portions 1203 act as insulating separators therefore in this embodiment the provision of a separation layer is not essential. Furthermore, the rigidity of the interacting sections, in terms of the rigid portions 1202 and 1205, has its rigidity further enhanced by the presence of relatively solid intermediate plates 1208.

Flexing of the construction shown in Figure 12A is substantially similar to that provided by the embodiment shown in Figure 11B. The flexing of the embodiment shown in Figure 12A is detailed in Figure 12B. Flexing occurs at the position of the relatively flexible portions 1203 and 1206. The rigidity of portions 1202 and 1205 is enhanced by the provision

of more solid plates 1208. Thus, the embodiment shown in Figures 12A and 12B may have more strenuous flexing forces applied thereto such that mechanical interaction detection is maintained even under severe operating conditions.

5       The provision of the flexible portions effectively provide lines over the surface of the conducting planes where folding is permitted. Thus, complex curvatures may be obtained by a number of folds being effected at a plurality of these preferred foldable lines, thereby allowing complex shapes to be attained while maintaining the desired electrical characteristics.

10       An alternative embodiment is shown in Figure 13 in which a first co-operating plane has flexible high resistive portions 1301 and rigid conducting portions 1302. This plane co-operates with a second plane 1303 of substantially homogenous construction. Thus, sufficient flexing and insulation is provided by the non-conducting flexible portions 1301 of the lower co-operating plane 1304. The rigidity of conducting portions 1302  
15       may be enhanced in a fashion substantially similar to that provided by Figure 12A as illustrated in Figure 14. The device includes an outer plane 1401 of substantially homogenous conducting construction. Below this, there is provided a second co-operating plane 1402 and the two planes  
20       may be separated by an insulating layer not shown in the example. The second plane or layer includes flexible non-conducting portions 1403 and more rigid conducting portions 1404, substantially similar to those shown in Figure 13. In addition, rigid plates 1405 are provided below each rigid portion 1404 thereby significantly enhancing the rigidity of these portions.  
25       Thus, the construction in Figure 14 is capable of withstanding more aggressive working environments compared to the lighter construction shown in Figure 13. In the construction shown in Figures 13 and 14 the outer layers, 1303 and 1401 respectively, are fabricated in a substantially elastic fashion, thereby providing for a stretching or extension of this layer  
30       during flexing operations.

The detector shown in Figure 1 is capable of accurately detecting the position of a mechanical interaction and as previously described, it is also possible to determine other characteristics of the mechanical interaction by modifying other electrical properties. A problem with the detector shown in Figure 1 is that it experiences difficulties if more than one unconnected mechanical interaction takes place. If a first mechanical interaction were to take place and, simultaneously, a second mechanical interaction were to take place, displaced from the first, it would not be possible, using the configuration shown in Figure 1, to identify the presence of two mechanical interactions. A condition would be detected to the effect that a mechanical interaction is taking place but the system would tend to perceive this as a single mechanical interaction having characteristics substantially similar to the average of the characteristics of the two independent interactions.

An alternative embodiment for overcoming problems of this type is shown in Figure 15. In Figure 15, a plurality of detectors 1501, 1502, 1503, 1504, 1505, 1506 and 1507 have been connected together and each of these individual detectors has its own unique connectors 1511, 1512, 1513 and 1514. In this way, each of the individual detectors may be connected to its own respective control circuit, such as circuit 121 shown in Figure 1 or, in an alternative embodiment, a single control circuit of the type shown in Figure 1 may be shared, using a switching arrangement, between all seven of the individual combined detectors. In this way, each individual detector, such as detector 1501, provides the same level of accuracy as the detector shown in Figure 1. However, if two or more mechanical interactions take place on different detector sections, it is possible to detect this condition and provide appropriate output responses. However, it is only possible to detect a plurality of mechanical interactions if these interactions take place on different sections and it is not possible for the embodiment shown in Figure 15 to detect a plurality of interactions if these interactions take place on the same section.



In the arrangement shown in Figure 15, the detectors have been arranged in strips such that there is enhanced definition in the direction of arrow 1521 but the definition in the direction of arrow 1522 has not changed.

5 In the detector shown in Figure 1, position detection is made possible using four electrical connection cables, a first two connected to opposing diagonal corners of the upper sheet and a further two connected to the alternative opposing diagonal corners of the lower sheet. An alternative configuration is shown in Figure 16 in which electrical  
10 connectors 1601, 1602, 1603 and 1604 are connected to respective corners 1611, 1612, 1613 and 1614 of a lower plane conducting sheet 1621. An upper plane conducting sheet 1622 is connected to a single detecting cable 1631 connected at a position 1632 towards an edge of upper conducting sheet 1622. A disadvantage of the configuration shown in  
15 Figure 16 is that five separate electrical connections are required whereas only four electrical connections are required in the configuration shown in Figure 1. However, in some circumstances, the configuration shown in Figure 16 does have advantages over that shown in Figure 1.

The configuration shown in Figure 16 may be used to effectively  
20 multiplex the operation of a detector so as to facilitate the detection of a plurality of mechanical interactions to a greater extent than the configuration shown in Figure 15. In particular, it facilitates detecting multiple mechanical interactions in both dimensions of the planar detector.

As shown in Figure 17, a lower planar sheet 1701 has connections  
25 1702, 1703, 1704 and 1705 at each of its corners. Thus, sheet 1701 operates in a way which is substantially similar to the operation of sheet 1621 and all output voltages are generated within this sheet, either across diagonal 1702 to 1704 or across diagonal 1703 to 1705, thereby giving a two-dimensional co-ordinate within the area of the sheet.

An upper planar sheet 1721 is divided into a plurality of portions. In the example shown, eight portions 1731 to 1738 are provided. Thus, the mechanical action results in conducting planes of at least one of said regions being brought into electrical interaction with the lower plane 1701. Furthermore, if a mechanical interaction occurs at region 1731 and a second mechanical interaction occurs at region 1735 (for example) both of these mechanical interactions may be determined independently and an output to this effect may be generated by a processing system, such as system 131.

In order to achieve the space division multiplexing provided by regions 1731 to 1738, time division multiplexing of the electrical signals is performed in which, during each individual time slot, one individual region 1731 to 1738 is considered. This is achieved by each individual region 1731 to 1738 having its own respective electrical connector 1741 to 1748. These connectors are preferably incorporated in to the structure of the sheet.

Control circuitry for the configuration shown in Figure 17 requires modification compared to that shown in Figure 2. In particular, each of the eight output control lines 1741 is supplied to its own respective buffering amplifier, similar to amplifiers 2223 and 2223 and the output from each of these eight amplifiers is applied to appropriate switching devices, allowing one of eight inputs to be selected using a plurality of switches substantially similar to switch 2221.

A complete scanning cycle consists of applying a voltage between input terminals 1702 and 1704. An output is then considered from each individual output terminals 1741 to 1748. The voltages are then reversed such that a voltage is applied between output terminals 1705 and 1703. Each of the individual input terminals is then considered again so as to provide two-dimensional co-ordinates within each of the individual regions 1731 to 1748. As described with respect to Figure 2, both voltages and

currents may be considered in order to provide additional mechanically related information, such as pressure related information etc.

5 In the detector configuration shown in Figure 1 and in alternative detector configurations, such as that shown in Figure 15 and that shown in Figure 16, it is necessary to provide electrical connection between processing equipment and the detector fabric itself. Techniques for the addition of electrical connectors to current conveying fabrics are known. However, in the known techniques, continual wear and usage of the detector assembly often results in electrical connectors becoming disconnected from the material fabric, resulting in total system failure. It is therefore highly desirable to provide a system in which the electrical connector is held very securely to the material fabric itself so as to provide a robust system which does not become disconnected through continual use.

15 An improved approach to providing electrical connection to the electric current carrying conductors within the fabric is illustrated in Figure 18. Further modification is shown in Figure 19. In both of these systems, the fabric is constructed from electrically conducting fibres and from electrically insulating fibres by a mechanical process, such as weaving or knitting. An improved electrical connection is achieved by connecting electrical connection devices to the electrically conducting fibres of the fabric forming the detector during the mechanical fabric generating process. Thus, in the embodiments shown in Figure 18 and Figure 19, there is no requirement for adding connectors after a fabric has been created. The provision of a connector to the electric current carrying fibres is achieved during the actual mechanical process itself. Thus, for example, if the fibres are being produced by a knitting operation, part of this knitting operation involves procedures by which the electrical current carrying connector is actually included as part of the overall knit.

Fibres 1801 making up the weave are illustrated in Figure 18. A weaving procedure may be considered as generating woven fabric by traversing in the direction of arrow 1802. At pre-programmed positions, or at manually selected positions, modifications are made to the weaving process to the effect that a connector 1803 is to be introduced.

In the example shown in Figure 18, connector 1803 is an insulation displacement connector (IDC) allowing an insulated wire to be connected in such a way that it is not necessary to remove the insulation from the wire, given that the insulation is effectively cut as the wire, illustrated by reference 1804 is inserted into the connector in the direction of arrow 1805.

The weaving procedure is modified such that connector 1803 is included as part of the weave and is thereby held relatively firmly after the weaving procedure has been completed. In order to provide a further enhanced mechanical connection between electrical connector 1803 and the remaining woven fabric, additional layers of electrically conducting epoxy resin 1805 and 1806 are applied, such that, in operation, physical force applied to connector 1803 such that the connector will not, under normal circumstances, be displaced from the woven material of the device and will maintain electrical integrity.

A similar configuration is shown in Figure 19 in which a rivet fastener 1901 is applied during a weaving or knitting process, thereby substantially embedding the rivet fastener within the overall weave or knit. After the rivet fastener has been secured by the woven fabric 1902, electrically conducting epoxy resin 1903 is applied to provide enhanced mechanical and electrical stability.

In the configuration shown in Figure 1 and in the configuration shown in Figure 16, an electrical field is established over the transmitting plane. Given a plane of infinite size, the electrical field would have a regular geometric distribution and the position of a mechanical interaction could be determined from two voltage measurements in a substantially

straightforward way. However, in the configuration shown in Figure 1 and Figure 16, edges are present and these edges introduce severe distortions to the nature of the electric field from which measurements are being taken. In the control circuit 121 and within the data processing system 132 it is possible to provide a level of compensation, possibly in response to empirical measurements but such an approach has disadvantages, one of which being a loss of resolution.

Systems are shown in Figures 20 and 21 in which a detector is constructed from fabric having electrically conductive elements to define at least two electrically conducting planes. The detector is configured to produce an electrical output in response to a mechanical interaction. The relationship between mechanical interaction and electrical output is enhanced by introducing a conductivity non-uniformity which is included in at least one of the planes so as to modify an electrical response to the mechanical interaction.

In Figure 20, an electrical connector 2001 is connected to a plane at a first corner and a second connector 2002 is connected to the diagonally opposing corner. A configuration of this type could be used for a detector of the type shown in Figure 1, in which the electrical field effectively traverses across the diagonal corners, resulting in distortions at the edges. In the embodiment shown in Figure 20, a conducting thread 2003 with relatively low resistivity is included across edge 2004, electrically connected to connector 2001. Similarly, a second conducting thread 2005, with relatively low resistivity, extends from electrical connection 2002 along edge 2006. In this way, the whole of edge 2004 becomes conducting and the whole of edge 2006 becomes conducting. The resulting electric field is then substantially linear throughout the length of the detector thereby substantially eliminating non-linear edge effects.

In its co-operating plane 2010 a low resistance conducting thread 2011 is included along edge 2012 and a similar conducting thread is

provided along the opposing edge. In this way, the electric field traverses in a direction which is orthogonal to the electric field provided in the upper sheet, thereby allowing co-ordinates defined in mutually orthogonal co-ordinate space.

5           A conducting material is shown in Figure 21 in which areas 2101, close to all four edges, have had their conductivity modified, such that the overall conductivity of the sheet is non-uniform. This modification to conductivity may be achieved in several ways, including the addition of a  
10           conducting thread of the type illustrated in Figure 20. Alternatively, the modification to conductivity, to provide conductivity non-uniformity, may be achieved by a printing operation in which electrically conducting inks, possibly including silicon, are printed at region 2101. Alternatively, the density of conducting fibres in the woven material itself may be modified towards the edges of the detector, again resulting in a conductivity non-  
15           uniformity. Furthermore, it should be appreciated that modifications of this type may be achieved using combinations of the above identified effects in order to tailor the required level of non-uniformity for a particular application.

20           In the configuration shown in Figure 1, a cycle is performed in which upper plane 102 effectively transmits allowing signals to be received by lower plane 103. A co-ordinate position is identified by reversing the operation of these planes, such that certain parts of the cycle include situations in which the lower plane 103 is effectively transmitting and the upper plane 102 is effectively transmitting. In a configuration of this type, it  
25           is preferable for the material types to be similar so as to provide substantially similar operations when plane 102 is transmitting or when plane 103 is transmitting. This is a particularly important constraint when the system is being used to measure current flow, given that different resistivities could be achieved in the different directions of current flow.

In the configuration shown in Figure 16, transmission always occurs from plane 1621, although in different orientations, and detection always occurs from plane 1622. With a configuration of this type, current always flows in the same direction therefore it is not essential for planes 1621 and  
5 1622 to have equivalent mechanical constructions.

In the configuration shown in Figure 16, a detector is constructed from fabric having electrically conductive elements to define at least two electrically conductive planes and configured to produce an electrical output in response to a mechanical interaction. A second electrically conductive  
10 plane, such as plane 1622 of the detector, has at least one electrical characteristic that differs significantly in value from the value of said characteristic of the first plane 1621.

In the detector shown in Figure 16, the upper receiving plane 1622 has a significantly lower resistance than the lower transmitting plane 1621.  
15 In this way, as the area of mechanical interaction increases, the amount of current flow increases significantly, thereby improving the definition of the system with respect to changes in the size of the mechanical interaction, and allowing for less intensive calculations when determining force etc.

## Claims

1. A detector constructed from fabric having electrically  
conductive elements to define at least two electrically conductive planes and  
5 configured to produce an electrical output in response to a mechanical  
interaction, wherein

a second electrically conductive plane of said detector has at least one  
electrical characteristic that differs significantly in value from the value of said  
characteristic of the first plane.

10

2. A detector according to claim 1, wherein one of said planes is  
used as a detector and voltages are applied sequentially in different  
directions to the other co-operating plane.

15

3. A detector according to claim 1 or claim 2, wherein said  
electrical characteristic is electrical resistance.

20

4. A position detector according to any of claims 1 to 3, wherein a  
second electrical property is determined to identify additional properties of  
said mechanical interactions.

25

5. A detector according to claim 4, configured to measure current  
or resistance at said second electrical property and configured to determine  
applied force, applied pressure, area of contact or orientation of an object as  
the additional property of said mechanical interactions.

30

6. A detector according to any of claims 1 to 5, wherein at least  
one of said planes includes first portions and second portions, said first  
portions having a higher resistance than said second portions and said first  
higher resistance portions being more flexible than said second portions.



7. A detector according to any of claims 1 to 6, wherein a detector surface is divided into a plurality of regions;

5 each of said regions includes a first conducting plane and a second conducting plane; and

a mechanical interaction results in conducting planes of at least one of said regions being brought closer together.

10 8. A detector according to any of claims 1 to 7, wherein said fabric has electrically conducting fibres and electrically insulating fibres, wherein electrical connection means are connected to said electrically conducting fibres of said fabric during a mechanical weaving or knitting process.

15 9. A detector according to any of claims 1 to 8, wherein a conductivity non-uniformity is included in at least one of said planes so as to modify an electrical response to a mechanical interaction.

20 10. A method of constructing a detector, comprising the steps of constructing electrically conductive elements from fabric to define at least two electrically conducting planes configured to produce electrical output in response to a mechanical interaction; and

configuring a second electrically conductive plane of said detector with at least one electrical characteristic that differs significantly in value from the value of said characteristic of said first plane.

25

11. A method of constructing a detector according to claim 10, wherein one of said planes is used as a detector and voltages are applied sequentially in different directions to the other co-operating plane.

12. A detector according to claim 10 or claim 11, wherein said electrical characteristic is electrical resistance.

5 13. A method according to any of claims 10 to 12, wherein a second electrical property is determined to identify additional properties of said mechanical interactions.

10 14. A method according to claim 13, wherein said detector is configured to measure current or resistance as said second electrical property and is configured to determine applied force, applied pressure, area of contact or orientation of an object as the additional property of said mechanical interactions.

15 15. A method according to any of claims 10 to 14, wherein at least one of said planes includes first portions and second portions, said first portions having a higher resistance than said second portions and said first higher resistance portions being more flexible than said second portions.

20 16. A method according to any of claims 10 to 15, wherein a detector surface is divided into a plurality of regions;

each of said regions includes a first conducting plane and a second conducting plane; and

a mechanical interaction resulting conducting planes of at least one of said regions being brought closer together.

25

30 17. A method according to any of claims 10 to 16, wherein said fabric has electrically conducting fibres and electrically insulating fibres, wherein electrical connection means are connected to said electrically conducting fibres of said fabric during a mechanical weaving or knitting process.

18. A method according to any of claims 10 to 17, wherein a conductivity non-uniformity is included in at least one of said planes so as to modify an electrical response to a mechanical interaction.



Application No: GB 9921925.5  
Claims searched: All

Examiner: Mark A Pullen  
Date of search: 20 January 2000

**Patents Act 1977**  
**Search Report under Section 17**

**Databases searched:**

UK Patent Office collections, including GB, EP, WO & US patent specifications, in:

UK CI (Ed.R): G1N (NACH, NACNR, NAEPR, NAGB8, NAGB10, NAGBR, NAQB),  
H1N (NUJD)

Int CI (Ed.7): G01L 1/20, G06K 11/12

Other: ONLINE : WPI, EPODOC, JAPIO

**Documents considered to be relevant:**

Category	Identity of document and relevant passage	Relevant to claims
A	GB 1308575 (DATA APPLIANCES CORP)	

X	Document indicating lack of novelty or inventive step	A	Document indicating technological background and/or state of the art
Y	Document indicating lack of inventive step if combined with one or more other documents of same category.	P	Document published on or after the declared priority date but before the filing date of this invention.
&	Member of the same patent family	E	Patent document published on or after, but with priority date earlier than, the filing date of this application.

# (12) UK Patent Application (19) GB (11) 2 341 933 (13) A

(43) Date of A Publication 29.03.2000

(21) Application No 9921925.5

(22) Date of Filing 17.09.1999

(30) Priority Data

(31) 9820910

(32) 26.09.1998

(33) GB

(71) Applicant(s)

Electrotextiles Company Limited  
(Incorporated in the United Kingdom)  
2 Bloomsbury Street, LONDON, WC1B 3ST,  
United Kingdom

(72) Inventor(s)

David Lee Sandbach

(74) Agent and/or Address for Service

Atkinson Burrington  
The Technology Park, Shirland Lane, SHEFFIELD,  
S9 3PA, United Kingdom

(51) INT CL<sup>7</sup>

G06K 11/12 // G01L 1/20

(52) UK CL (Edition R )

G1N NAQB N1A3B N1D9 N7H2 N7S

H1N NBH NUJD N449 N618 N705 N707 N744 N854

(56) Documents Cited

GB 1308575 A

(58) Field of Search

UK CL (Edition R ) G1N NACH NACNR NAEPR NAGBR

NAGB10 NAGB8 NAQB , H1N NUJD

INT CL<sup>7</sup> G01L 1/20 , G06K 11/12

ONLINE : WPI, EPODOC, JAPIO

(54) Abstract Title

**Position detector constructed from conductive fabric**

(57) A position detector comprises at least two planes 1621, 1622 of electrically conductive fabric, at least one of the planes having an electrical characteristic eg resistance which differs significantly in value from that of the first plane. A mechanical interaction on the surface brings opposed planes together and results in an electrical output. One of the planes is used as a detector whilst voltages are applied sequentially in different directions to a co-operating plane. Current flow between planes increases significantly with an increase in the area of mechanical interaction, thereby improving the definition of the detector. A second electrical characteristic may be used to identify additional properties of a mechanical interaction eg applied force, area of contact or orientation of an object. The fabric can be woven (Fig.4), non-woven eg felt or knitted and can combine conductive and insulative fibres. Electrical signals can be derived independently by Time Division Multiplexing TMD (Fig. 3) via a micro-controller (201, Fig.2) operated circuit (121, Fig.2).




Figure 16

GB 2 341 933 A





Figure 1



**Figure 2**

3/19




Figure 3



4/19




Figure 4

5/19




Figure 5

6/19




Figure 6

7/19




Figure 7




Figure 8







Figure 9


10/19

*Figure 10*

11/19





*Figure 11A*



*Figure 11B*



12/19



13/19




Figure 13

14/19




Figure 14

15/19




Figure 15




Figure 16

17/19






Figure 17

18/19

*Figure 18**Figure 19*

19/19




Figure 20




Figure 21



## Detector Constructed From Fabric

5 The present invention relates to a detector constructed from fabric having electrically conductive elements to define at least two electrically conductive planes.

A fabric touch sensor for providing positional information is described in United States patent 4,659,873 of Gibson. The sensor is fabricated using two layers of fabric having conducting threads, separated by a resistive layer to prevent unintentional contact.

10 An improvement to this known configuration is proposed in the applicant's co-pending British patent application number 98 20 902 in which there is provided a position detector constructed from fabric having electrically conductive elements, comprising at least two electrically conductive planes. A potential is applied across at least one of the planes to determine the position of a mechanical interaction. In addition, a second  
15 electrical property is determined, such as current, to identify additional properties to the mechanical interaction, such as an applied force, an applied pressure or an area of contact.

20 A further proposal is included in the applicant's co-pending British patent application number 98 20 905 in which there is provided a detector constructed from fabric having electrically conductive elements defining at least two electrically conductive planes and configured to produce electrical outputs in response to mechanical interactions. At least one of the planes includes first portions and second portions, wherein the first portions have a  
25 higher resistance than the second portions and the first higher resistance portions are more flexible than the second portions.

30 A third proposal is described in the applicant's co-pending British patent application number 98 20 906, in which there is provided a detector constructed from fabric having electrically conductive elements and configured to produce electrical outputs in response to mechanical

interactions. The detector surface is divided into a plurality of regions and each of these regions includes a first conducting plane and a second conducting plane. A mechanical interaction results in conducting planes of at least one of said regions being brought closer together.

5           A fourth proposal is described in the applicant's co-pending British patent application number 98 20 908 in which there is provided a fabric constructed from a electrically conducting fibres and from electrically insulating fibres by a mechanical process. Electrical connection means are connected to electrically conducting fibres of the fabric during the  
10           mechanical process. Thus, the fourth improvement provides for securely attaching electrical connectors to electrically conducting fibres, thereby reducing the risk of said connectors becoming detached during use of the detector.

          A fifth improvement is disclosed in the applicant's co-pending British  
15           patent application number 98 20 909, in which there is provided a detector constructed from fabric having electrically conductive elements to define at least two electrically conductive planes and configured to produce an electrical output in response to a mechanical interaction, wherein a conductivity non-uniformity is included in at least one of said planes so as to  
20           modify an electrical response to a mechanical interaction.

          According to a first aspect of the present invention, there is provided a detector constructed from fabric having electrically conductive elements to define at least two electrically conductive planes and configured to produce an electrical output in response to a mechanical interaction, wherein a  
25           second electrically conductive plane of said detector has at least one electrical characteristic that differs significantly in value from the value of said characteristic of the first plane.

          In a preferred embodiment, one of the planes is used as a detector and voltages are applied sequentially in different directions to other co-  
30           operating plane. Preferably, the electrical characteristic is electrical

resistance.

According to a second aspect of the present invention, there is provided a method of constructing a detector, comprising the steps of constructing electrically conductive elements from fabric to determine at least  
5 two electrically conducting planes configured to produce electrical output in response to a mechanical interaction; and configuring a second electrically conductive plane of said detector with at least one electrical characteristic that differs significantly in value from the value of said characteristic of said first plane.

10 The invention will be described by way of example only, with reference to the accompanying drawings of which:

Figure 1 shows a position detector constructed from fabric;

Figure 2 shows a control circuit identified in Figure 1;

15 Figure 3 details operations performed by the micro-controller identified in Figure 2;

Figure 4 details planes identified in Figure 1;

Figure 5 details current flow due to mechanical interaction;

Figure 6 details an alternative construction for conducting fabric  
planes;

20 Figure 7 shows an alternative configuration of conducting planes;

Figure 8 shows an alternative configuration of conducting planes;

Figure 9 details a composite configuration of conducting planes; and

Figure 10 shows an asymmetric object interacting with conducting  
planes.

25 Figure 11A and Figure 11B show an alternative construction for a detector;

Figure 12A and Figure 12B show a further alternative construction;

Figure 13 shows a further alternative construction;

Figure 14 shows a further alternative construction.

Figure 15 shows an alternative embodiment having a plurality of detectors;

Figure 16 shows an alternative detector configuration; and

Figure 17 shows multiple detectors of the type shown in Figure 16.

5 Figure 18 shows a first embodiment in which a connector has been included during the machining process; and

Figure 19 shows an alternative embodiment in which a connector has been added during a machining process.

10 Figure 20 shows a detector constructed from fabric having a conductivity non-uniformity; and

Figure 21 shows an alternative embodiment with a conductivity non-uniformity.

A position detector 101 constructed from fabric is shown in Figure 1. The detector has two electrically conducting fabric planes, in the form of a first plane 102 and a second plane 103. The planes are separated from each other and thereby electrically insulated from each other, by means of an insulating mesh 104. When force is applied to one of the planes, the two conducting planes are brought together, through the mesh 104, thereby creating a position at which electrical current may conduct between planes 102 and 103. In this way, it is possible to identify the occurrence and/or position of a mechanical interaction.

20 The fabric planes are defined by fabric structures, which may be considered as a woven, non-woven (felted) or knitted etc. The fabric layers may be manufactured separately and then combined to form the detector or the composite may be created as part of the mechanical construction process.

25 When a voltage is applied across terminals 107 and 108, a voltage gradient appears over plane 102. When a mechanical interaction takes place, plane 103 is brought into electrical contact with plane 102 and the actual voltage applied to plane 103 will depend upon the position of the

30

interaction. Similarly when a voltage is applied between connectors 111 and 112, a voltage gradient will appear across plane 103 and mechanical interaction will result in a voltage being applied to plane 102. Similarly, the actual voltage applied to plane 102 will depend upon the actual position of the interaction. In this way, for a particular mechanical interaction, it is possible to identify locations within the plane with reference to the two aforesaid measurements. Thus, connectors 107, 108, 111 and 112 are received by a control circuit 121, configured to apply voltage potentials to the detector 101 and to make measurements of electrical properties in response to mechanical interactions.

Control circuit 121 identifies electrical characteristics of the sensor 101 and in response to these calculations, data relating to the characteristics of the environment are supplied to a data processing system, such as a portable computer 131, via a conventional serial interface 131.

Control circuit 121 is detailed in Figure 2. The control circuit includes a micro-controller 201 such as a Philips 80C51 running at a clock frequency of twenty megahertz. Operations performed by micro-controller 201 are effected in response to internally stored commands held by an internal two kilobyte read-only memory. The micro-controller also includes one hundred and twenty-eight bytes of randomly accessible memory to facilitate intermediate storage while performing calculations. Micro-controller 201 includes a serial interface 202 in addition to assignable pins and an interface for communicating with an analogue to digital converter 203, arranged to convert input voltages into digital signals processable by the micro-controller 201.

The control circuit 121 includes two PNP transistors 211 and 212, in addition to four NPN transistors 213, 214, 215 and 216. All of the transistors are of relatively general purpose construction and control switching operations within the control circuit so as to control the application

of voltages to the position detector 101.

In operation, measurements are made while a voltage is applied across first plane 102 and then additional measurements are made while a voltage is applied across the second plane 103; and output voltage only being applied to one of the planes at any particular time. When an output voltage is applied to one of the planes, plane 102 or plane 103, input signals are received from the co-operating plane 103 or 102 respectively. Input signals are received by the analogue to digital converter 203 via a selection switch 221, implemented as a CMOS switch, in response to a control signal received from pin C6 of the micro-controller 201. Thus, in its orientation shown in Figure 2, switch 221 has been placed in a condition to receive an output from a first high impedance buffer 222, buffering an input signal received from plane 102. Similarly, when switch 221 is placed in its alternative condition, an input is received from a second high impedance buffer 223, configured to receive an input signal from plane 103. By placing buffers 222 and 223 on the input side of CMOS switch 221, the switch is isolated from high voltage electrostatic discharges which may be generated in many conditions where the detector undergoes mechanical interactions.

In the condition shown in Figure 2, switch 221 is placed in its upper condition, receiving input signals from buffer 222, with output signals being supplied to the second plane 103. Further operation will be described with respect to this mode of operation and it should be appreciated that the roles of the transistor circuitry is reversed when switch 221 is placed in its alternative condition. As previously stated, condition selection is determined by an output signal from pin C6 of micro-controller 201. In its present condition the output from pin C6 is low and switch 221 is placed in its alternative configuration when the output from pin 6 is high.

Output pin C0 controls the conductivity of transistor 211 with pins C1 to C5 having similar conductivity control upon transistors 212, 213, 214, 215 and 216 respectively.

Transistors 211 and 213 are switched on when a voltage is being applied to the first plane 102 and are switched off when a voltage is being applied to the second plane 103. Similarly, when a voltage is being applied to the second plane 103, transistors 212 and 215 are switched on with transistors 211 and 213 being switched off. In the configuration shown in Figure 2, with switch 221 receiving an input from buffer 222, output transistors 211 and 213 are switched off with output transistors 212 and 215 being switched on. This is achieved by output pin C0 being placed in a high condition and pin C1 being placed in a low condition. Similarly, pin C3 is placed in a low condition and pin C4 is placed in a high condition.

In the configuration shown, C3 is placed in a low condition, as previously described. The micro-controller 201 includes a pull-down transistor arranged to sink current from the base of transistor 212, resulting in transistor 212 being switched on to saturation. Consequently, transistor 212 appears as having a very low resistance, thereby placing terminal 111 at the supply voltage of five volts. Resistor 231 (4K7) limits the flow of current out of the micro-controller 201, thereby preventing burn-out of the micro-controller's output transistor.

Pin C4 is placed in a high state, resulting in transistor 215 being placed in a conducting condition. A serial resistor is not required given that the micro-controller 201 includes internal pull-up resistors, as distinct from a pull-up transistor, such that current flow is restricted. Thus, transistors 212 and 215 are both rendered conductive, resulting in terminal 111 being placed at the positive supply rail voltage and terminal 112 being placed at ground voltage. The capacitors shown in the circuit, such as capacitor 219, limit the rate of transistor transitions thereby reducing rf transmissions from the sensor 101.

With transistors 212 and 215 placed in their conductive condition, input signals are received from the first plane 102 in the form of a voltage applied to terminal 108. For position detection, this voltage is measured

directly and transistor 214 is placed in a non-conductive condition by output pin C2 being placed in a low condition. Under these conditions, the voltage from input terminal 108 is applied to analogue to digital converter 203 via buffer 222 and switch 221.

5           In accordance with the present invention, a second electrical property is determined which, in this embodiment, represents the current flowing through the sensor in response to a mechanical interaction. The current measurement is made by placing transistor 215 in a conductive condition, by placing output pin C4 in a high condition. In this condition,  
10           current received at terminal 108 is supplied to transistor 214 via resistor 214A, having a resistance of typically 5k selectable so as to correspond to the characteristics of the sensor. A voltage is supplied to A to D converter 203 via buffer 222 and switch 221 but on this occasion the voltage represents a voltage drop, and hence a current, across resistor 214A.

15           Thus, transistors 212 and 215 are placed in a conducting condition, transistor 214 is placed in a non-conducting condition, so as to measure voltage, and is then placed in a conducting condition so as to measure current. The roles of the transistors are then reversed, such that output transistors 211 and 213 are placed in a conducting condition, with  
20           transistors 212 and 215 being placed in a non-conducting condition (and switch 221 reversed) allowing a voltage to be measured by placing transistor 216 in a non-conducting condition, and then allowing a current to be measured by placing transistor 216 in a conducting condition.

          The cycling of line conditions, in order to make the measurements  
25           identified previously, is controlled by a clock resident within micro-controller 201. After each condition has been set up, a twelve bit number is received from the digital to analogue converter 203 and this number is retained within a respective register within micro-controller 201. Thus, after completing a cycle of four measurements, four twelve bit values are stored  
30           within the micro-controller 201 for interrogation by the processing device



131. Furthermore, the rate of cycling may be controlled in response to instructions received from the processing device 131.

Operations performed by micro-controller 201 are detailed in Figure 3. The micro-controller continually cycles between its four configuration states and each time a new input is produced, representing a current or a voltage in one of the two configurations, new output data is calculated on an on-going basis. Thus, output registers are updated such that the best data is made available if the micro-controller is interrupted by the external processor 131.

The micro-controller 201 is fully interrupt driven in terms of receiving external interrupts for data interrogation along with internal interrupts in order to initiate a configuration cycle. The external interrupt has a higher priority such that external processor 131 is provided with information as soon as possible in response to making an interrupt request.

Internally interrupts for the micro-controller 201 are generated by its own internal timer and the procedure shown in Figure 3 is effectively held in a wait state until a next timer interrupt is received at step 301. The wait state allows voltage levels on connections 107, 108, 111 and 112 to become stable and provides sufficient time for valid data to be received from the analogue to digital converter 203.

At step 302, an output is received from analogue to digital converter 203 and at step 303 calculations are performed with respect to the most current data received from the analogue to digital converter, so as to convert numerical values relating to voltages and currents into numerical values representing properties of the mechanical interaction. Thus, after performing calculations at step 303, appropriate registers are updated at step 304 and it is these registers that are interrogated in response to an interrupt received from processing system 131.

At step 305 next conditions for the output lines are set by appropriate logic levels being established for output pins C0 to C6. After the

next output condition has been selected, the processor enters a wait state at step 306, allowing the electrical characteristics to settle, whereafter processing continues in response to the next timer interrupt.

Thus, it should be appreciated that on each iteration of the procedure shown in Figure 3, one of the output conditions is selected at step 305. Thus, it should be appreciated that the input data is effectively delayed and does not represent a condition of the electrical characteristics at an instant. If in practice, the delay between measurements becomes too large, it becomes necessary to enhance the frequency of operation of circuits within the control system shown in Figure 2. Thus, the rate of conversion for converter 203 would need to be increased and the circuitry would need to be redesigned for high frequency operation. This in turn could create problems in terms of high frequency interference resulting in enhanced shielding being required for the facility as a whole.

When output condition number one is selected, an output voltage at 108 is determined. On the next cycle, identified as output condition number two, the current flowing through connector 108 is determined. On the next iteration, under output configuration number three, the voltage appearing at connector 112 is determined and on the next cycle, identified as condition number four, the current flowing through connector 112 is determined. After each of these individual measurements, new data is generated in response to steps 303 and 304 such that resulting output registers are being regularly updated on a continual basis, such that the processing system 131 may effectively perform a continual monitoring operation in terms of changes made to the mechanical interactions with the detector 101.

In a typical implementation, the four characteristic measurements, making up a complete cycle, will be repeated at a frequency of between twenty-five to fifty times per second. In situations where such a repetition rate is not required, it may be preferable to increase the duration of the wait states and thereby significantly reduce overall power consumption.

Planes 102, 103 and 104 of the detector 101 are detailed in Figure 4. Planes 101 and 103 are of substantially similar construction and are constructed from fabric having electrically conductive elements 402 in plane 102 along with similar electrical conductive elements 403 in plane 103. Thus, it is possible for a voltage indicative of position to be determined when conductive elements 402 are placed in physical contact with conductive elements 403.

The overall resistivity of planes 402 and 403 are controlled by the inclusion of non-conducting elements 404 and 405. Thus, resistivity is controlled by controlling the relative quantities and/or densities of conductive elements 402 with non-conductive elements 404. Resistivity may also be controlled by selecting an appropriate fibre type, adjusting the thickness of the fibre or adjusting the number of strands present in a yarn.

Plane 404 represents a non-conducting insulating spacer positioned between the two conducting planes 102, and 103. Plane 104 is constructed as a moulded or woven nylon sheet having an array of substantially hexagonal holes 411, the size of holes 411 is chosen so as to control the ease with which it is possible to bring conductive elements 402 into physical contact with conductive elements 403. Thus, if relatively small holes 411 are chosen, a greater force is required in order to bring the conductive elements together. Similarly, if the size of the hole is increased, less force is required in order to achieve the conductive effect. Thus, the size of holes 411 would be chosen so as to provide optimal operating conditions for a particular application. Operating conditions may also be adjusted by controlling the thickness of layer 104, its surface flexibility and the contour of co-operating planes 102 and 103.

When a potential is applied across one of the conducting planes, the actual potential detected at a point on that plane will be related to the position at which the measurement is made. Thus, a direct voltage measurement from the co-operating plane gives a value from which a

positional co-ordinate may be determined. By reversing the plurality of the planes and taking a measurement from the opposing plane, two co-ordinates are obtained from which it is then possible to identify a precise location over the planar surface.

5 In addition to measuring position on the planar surface, the present invention is directed at identifying additional electrical properties in order to determine properties of the mechanical interaction. As previously described, the system is configured to measure currents in addition to measuring voltages.

10 When the two conducting planes are brought into mechanical contact, due to a mechanical interaction, the amount of current flowing as a result of this contact will vary in dependence upon the actual position of the plane where the mechanical interaction takes place. The position of the mechanical interaction has also been determined with reference to voltages  
15 and it could be expected that these two quantities will vary in a substantially similar way, each representing the same physical situation. Experience has shown that variations in measured current do not follow exactly the same characteristic as variations in measured voltage. As illustrated in Figure 5, the amount of current flowing due to a mechanical interaction will depend  
20 upon the position of a mechanical interaction 501. However, in addition to this, the amount of current flow will also depend upon the size of the mechanical interaction. As the size of the mechanical interaction increases, there is a greater area of contact and as such the overall resistance of the mechanical interaction is reduced. However, it should be appreciated that  
25 variations in terms of current with respect to interaction size is a sophisticated relationship, given that, in addition to the resistivity of the contact area 501, the resistivity of the actual electrical connections within the sheet must also be taken into account.

30 Thus, current is transmitted through a region 502 in order to provide a current to the contact region 501. Some aspects of this effect will be

compensated with reference to position calculations and other variations due to this effect may be compensated by a non-linear analysis of the input data.

5           Contact area resistivity is illustrated generally at 510 and shows that the amount of current flowing between plane 102 and plane 103 is considered as being related to the area of mechanical interaction, which is related to the area of contact externally and to the level of externally applied mechanical force.

10           The resulting non-linear relationship between the force area product and the resulting current flow is illustrated generally at 520. At 521 there is an initial threshold point, identifying the point at which the gap starts to be closed, followed by an operational part of the curve which may give useful indications of pressure up to point 522, whereafter the relationship becomes very non-linear until position 523 where the relationship effectively  
15           saturates.

          Using a detector of the type illustrated in Figure 1, it is possible to measure current flow, which could also be considered as contact resistance, in order to identify an additional mechanical property of the interaction. As illustrated in Figure 5, this other mechanical property is  
20           related to the area of contact between the sheets, determined by the amount of force applied to the sheets, and to the total area over which the force is applied; or a combination of these two properties. Thus, data relating to force and area may give useful information relating to the interaction, separate from the position at which the interaction takes place.

25           In some situations, such as when using a stylus or similar implement, the area of applied force remains substantially constant therefore a measurement of current will enable calculations to be made in terms of stylus pressure. Pressure sensitive styli are known but in known configurations the pressure detection is determined within the stylus itself,  
30           leading to the stylus being mechanically connected to operational

equipment or requiring sophisticated wireless transmission within the stylus itself. The present embodiment allows stylus pressure to be determined using any non-sophisticated stylus, given that the pressure detection is made by the co-operating fabric detector, arranged to detect stylus position (with reference to voltage) in combination with stylus pressure, with  
5 reference to current.

An alternative construction for the conducting fabric planes is illustrated in Figure 6. The detector includes a first conducting plane 601 and a second conducting plane 602. In addition, woven into each of the  
10 conducting planes 601 and 602, there are a plurality of non-conducting nodes 605 arranged to mutually interfere and thereby separate the two conducting planes. Between the nodes, the fabrics of the first and second planes may be brought into contact relatively easily such that the application of force, illustrated by arrow 611 would tend to cause a finite  
15 number of regions interspersed between nodes 605 to be brought into contact. Thus, for a particular region, contact either is taking place or is not taking place as illustrated by curve 621.

With a number of such regions brought into contact, the overall level of current flow will tend to vary with the area of contact as illustrated by  
20 curve 631. Thus, using a construction of the type shown in Figure 6, it is possible to obtain a more linear relationship, compared to that shown in Figure 5, in which the level of current flow gives a very good indication of the area of coverage as distinct from the level of force applied to the mechanical interaction.

Given a construction of the type shown in Figure 6, an indication of applied force or pressure may be obtained, in addition to an accurate determination of area, by providing an incremental switching operation. In the configuration shown in Figure 7, there is provided a first conducting plane 701 which interacts with a second conducting plane 702.  
25 Furthermore, conducting plane 702 interacts with a third conducting plane  
30

704. Conducting plane 701 is separated from conducting plane 702 by non-conducting portions 705. Similarly, plane 702 is separated from plane 704 by non-conducting portions 706. More non-conducting portions 705 are provided than similar non-conducting portions 706. Consequently, less  
5 force is required to produce electrical contact between planes 701 and 702 than is required to produce an electrical contact between planes 702 and 704. In this way, it is possible to provide an incremental measurement of force, given that a low force will only cause contact between plane 701 and plane 702 whereas a larger force will also provide electrical contact  
10 between plane 702 and 704.

An alternative configuration is shown in Figure 8 in which it is possible to obtain enhanced substantially continuous variations in current flow with respect to applied force. A first conducting plane 801 interacts with a second conducting plane 802. The planes are woven in such a way as to  
15 produce very uneven surfaces such that, under light load, the level of interaction is relatively low. As load increases, as illustrated generally at 805, a greater level of surface contact shown at 806 is created thereby increasing the level of current flow in a substantially continuous way. It should also be noted that this configuration does not include an insulating  
20 layer as such and that a level of current flow will always take place even under conditions of zero load. Alternatively, a very thin insulating layer could be provided, having a relatively low threshold, thereby resulting in a zero current flow when no load is applied.

As shown by curve 811, the output current varies with respect to  
25 variations in applied force for a constant load area. Similarly, as shown by curve 821, output current varies with respect to load area for a substantially constant applied force.

A composite configuration is shown in Figure 9, in which a detector  
30 901, substantially similar to that shown in Figure 6, is combined with a detector 902, substantially similar to that shown in Figure 9. Detector 901

provides an accurate measurement of applied area and it is relatively unaffected by applied force. Detector 902, as shown in Figure 8, provides an output which varies with respect to area and force. Thus, by processing the output of these two detectors in combination, it is possible to  
5 compensate the output from detector 902 in order to produce values representing force, such that the two currents provide indications of both force and area.

The operation of the control circuit 121 is such as to apply a first voltage across diagonals 107 and 108 with a similar voltage being applied  
10 across diagonals 111 and 112. The nature of the voltage distribution is therefore asymmetric, but this does not result in difficulties provided that the area of contact between the two planes is relatively symmetric. However, should an asymmetric area of contact be made, as illustrated in Figure 10, differences will occur in terms of current measurements when considering  
15 calculations made in the two directions.

An asymmetric object 1001 is shown applied to the surface of a detector 1002. When a voltage is applied between contact 107 and 108, paths over which current may flow, illustrated generally at 1003 are relatively large and the object is perceived as having a large area or is  
20 perceived as applying a large force. In the opposite dimension, when a voltage is applied between 111 and 112, the regions over which current flow takes place illustrated generally at 1105, become relatively smaller therefore the object would be perceived as having a relatively smaller area or would be perceived as providing a relatively smaller force.

25 If the system is programmed to the effect that the object has a constant area and applies a constant force, these differences in terms of current flow may be processed in order to give an indication as to the orientation of the object. Thus, the system of the type illustrated in Figure 10, is used in combination with the detector of the type illustrated in Figure  
30 9 it is possible to make reference to the parameters of location in two-



dimensions, force or pressure, the area of application and orientation.

In the preferred embodiment, electrical characteristics of voltage and current are measured. Alternatively, it would be possible to determine the resistance or the resistivity of the conducting sheets. Problems may be encountered when using alternating currents due to energy being radiated from the conducting sheets. However, in some situations it may be preferable to use alternating currents, in which further electrical characteristics of the detector may be considered, such as capacitance, inductance and reactance etc.

The detector shown in Figure 1, constructed from conducting planes 102 and 103, operates satisfactorily if the plane of the detector is maintained substantially flat. This does not create a problem in many applications where relatively flat operation is considered desirable. However, although constructed from fabric, thereby facilitating bending and folding operations, the reliability of the detector in terms of its electrical characteristics cannot be guaranteed if the detector planes are folded or distorted beyond modest operational conditions.

A detector is shown in Figure 11, constructed from fabric having electrically conductive elements to define at least two electrically conductive planes. The detector is configured to produce an electrical output in response to a mechanical interaction, as illustrated in Figure 1. At least one of the planes includes first portions and second portions in which the first portions have a higher resistance than said second portions and the first higher resistance portions are more flexible than the second portions. In this way, flexing occurs at the portions of high resistance, where contact between the planes has little effect, while the lower resistance portions, where contact does have a strong electrical effect, remain substantially rigid such that the flexing of the material does not occur over these portions of the detector.

Portions 1101 have a relatively high resistance compared to portions 1102. Portions 1101 are not involved in terms of creating an electrical reaction in response to a mechanical interaction. The electrical responses are provided by the more rigid weave of portions 1102. The purpose of portions 1101 is detailed in Figure 11B. A curvature has been applied to the detector but the configuration is such that normal operation is still possible. The flexing has occurred predominantly at portions 1101. However, portions 1102 have remained straight thereby ensuring that they remain displaced from each other, even when a curvature is present, such that the detector is still available for detecting the presence of a mechanical interaction.

The rigidity of portions 1102 may be enhanced as shown in Figure 12A. A first plane 1201 has rigid portions 1202 and flexible portions 1203. A second plane 1204 has relatively rigid portions 1205 and relatively flexible portions 1206. The relatively flexible portions 1206 physically contact against similar portions 1203 in the first plane 1201. In order to ensure that there is no, or at least minimal electrical interaction at these points of contacts, the electrical resistance of the flexible portions 1203 and 1206 is relatively high. A partially insulating layer may be provided between the conducting layers, as shown in Figure 1. However, the flexible portions 1203 act as insulating separators therefore in this embodiment the provision of a separation layer is not essential. Furthermore, the rigidity of the interacting sections, in terms of the rigid portions 1202 and 1205, has its rigidity further enhanced by the presence of relatively solid intermediate plates 1208.

Flexing of the construction shown in Figure 12A is substantially similar to that provided by the embodiment shown in Figure 11B. The flexing of the embodiment shown in Figure 12A is detailed in Figure 12B. Flexing occurs at the position of the relatively flexible portions 1203 and 1206. The rigidity of portions 1202 and 1205 is enhanced by the provision

of more solid plates 1208. Thus, the embodiment shown in Figures 12A and 12B may have more strenuous flexing forces applied thereto such that mechanical interaction detection is maintained even under severe operating conditions.

5       The provision of the flexible portions effectively provide lines over the surface of the conducting planes where folding is permitted. Thus, complex curvatures may be obtained by a number of folds being effected at a plurality of these preferred foldable lines, thereby allowing complex shapes to be attained while maintaining the desired electrical characteristics.

10       An alternative embodiment is shown in Figure 13 in which a first co-operating plane has flexible high resistive portions 1301 and rigid conducting portions 1302. This plane co-operates with a second plane 1303 of substantially homogenous construction. Thus, sufficient flexing and insulation is provided by the non-conducting flexible portions 1301 of the lower co-operating plane 1304. The rigidity of conducting portions 1302  
15       may be enhanced in a fashion substantially similar to that provided by Figure 12A as illustrated in Figure 14. The device includes an outer plane 1401 of substantially homogenous conducting construction. Below this, there is provided a second co-operating plane 1402 and the two planes  
20       may be separated by an insulating layer not shown in the example. The second plane or layer includes flexible non-conducting portions 1403 and more rigid conducting portions 1404, substantially similar to those shown in Figure 13. In addition, rigid plates 1405 are provided below each rigid portion 1404 thereby significantly enhancing the rigidity of these portions.  
25       Thus, the construction in Figure 14 is capable of withstanding more aggressive working environments compared to the lighter construction shown in Figure 13. In the construction shown in Figures 13 and 14 the outer layers, 1303 and 1401 respectively, are fabricated in a substantially elastic fashion, thereby providing for a stretching or extension of this layer  
30       during flexing operations.

The detector shown in Figure 1 is capable of accurately detecting the position of a mechanical interaction and as previously described, it is also possible to determine other characteristics of the mechanical interaction by modifying other electrical properties. A problem with the detector shown in Figure 1 is that it experiences difficulties if more than one unconnected mechanical interaction takes place. If a first mechanical interaction were to take place and, simultaneously, a second mechanical interaction were to take place, displaced from the first, it would not be possible, using the configuration shown in Figure 1, to identify the presence of two mechanical interactions. A condition would be detected to the effect that a mechanical interaction is taking place but the system would tend to perceive this as a single mechanical interaction having characteristics substantially similar to the average of the characteristics of the two independent interactions.

An alternative embodiment for overcoming problems of this type is shown in Figure 15. In Figure 15, a plurality of detectors 1501, 1502, 1503, 1504, 1505, 1506 and 1507 have been connected together and each of these individual detectors has its own unique connectors 1511, 1512, 1513 and 1514. In this way, each of the individual detectors may be connected to its own respective control circuit, such as circuit 121 shown in Figure 1 or, in an alternative embodiment, a single control circuit of the type shown in Figure 1 may be shared, using a switching arrangement, between all seven of the individual combined detectors. In this way, each individual detector, such as detector 1501, provides the same level of accuracy as the detector shown in Figure 1. However, if two or more mechanical interactions take place on different detector sections, it is possible to detect this condition and provide appropriate output responses. However, it is only possible to detect a plurality of mechanical interactions if these interactions take place on different sections and it is not possible for the embodiment shown in Figure 15 to detect a plurality of interactions if these interactions take place on the same section.

In the arrangement shown in Figure 15, the detectors have been arranged in strips such that there is enhanced definition in the direction of arrow 1521 but the definition in the direction of arrow 1522 has not changed.

5 In the detector shown in Figure 1, position detection is made possible using four electrical connection cables, a first two connected to opposing diagonal corners of the upper sheet and a further two connected to the alternative opposing diagonal corners of the lower sheet. An alternative configuration is shown in Figure 16 in which electrical  
10 connectors 1601, 1602, 1603 and 1604 are connected to respective corners 1611, 1612, 1613 and 1614 of a lower plane conducting sheet 1621. An upper plane conducting sheet 1622 is connected to a single detecting cable 1631 connected at a position 1632 towards an edge of upper conducting sheet 1622. A disadvantage of the configuration shown in  
15 Figure 16 is that five separate electrical connections are required whereas only four electrical connections are required in the configuration shown in Figure 1. However, in some circumstances, the configuration shown in Figure 16 does have advantages over that shown in Figure 1.

20 The configuration shown in Figure 16 may be used to effectively multiplex the operation of a detector so as to facilitate the detection of a plurality of mechanical interactions to a greater extent than the configuration shown in Figure 15. In particular, it facilitates detecting multiple mechanical interactions in both dimensions of the planar detector.

25 As shown in Figure 17, a lower planar sheet 1701 has connections 1702, 1703, 1704 and 1705 at each of its corners. Thus, sheet 1701 operates in a way which is substantially similar to the operation of sheet 1621 and all output voltages are generated within this sheet, either across diagonal 1702 to 1704 or across diagonal 1703 to 1705, thereby giving a two-dimensional co-ordinate within the area of the sheet.

An upper planar sheet 1721 is divided into a plurality of portions. In the example shown, eight portions 1731 to 1738 are provided. Thus, the mechanical action results in conducting planes of at least one of said regions being brought into electrical interaction with the lower plane 1701. Furthermore, if a mechanical interaction occurs at region 1731 and a second mechanical interaction occurs at region 1735 (for example) both of these mechanical interactions may be determined independently and an output to this effect may be generated by a processing system, such as system 131.

In order to achieve the space division multiplexing provided by regions 1731 to 1738, time division multiplexing of the electrical signals is performed in which, during each individual time slot, one individual region 1731 to 1738 is considered. This is achieved by each individual region 1731 to 1738 having its own respective electrical connector 1741 to 1748. These connectors are preferably incorporated in to the structure of the sheet.

Control circuitry for the configuration shown in Figure 17 requires modification compared to that shown in Figure 2. In particular, each of the eight output control lines 1741 is supplied to its own respective buffering amplifier, similar to amplifiers 2223 and 2223 and the output from each of these eight amplifiers is applied to appropriate switching devices, allowing one of eight inputs to be selected using a plurality of switches substantially similar to switch 2221.

A complete scanning cycle consists of applying a voltage between input terminals 1702 and 1704. An output is then considered from each individual output terminals 1741 to 1748. The voltages are then reversed such that a voltage is applied between output terminals 1705 and 1703. Each of the individual input terminals is then considered again so as to provide two-dimensional co-ordinates within each of the individual regions 1731 to 1748. As described with respect to Figure 2, both voltages and

currents may be considered in order to provide additional mechanically related information, such as pressure related information etc.

In the detector configuration shown in Figure 1 and in alternative detector configurations, such as that shown in Figure 15 and that shown in Figure 16, it is necessary to provide electrical connection between processing equipment and the detector fabric itself. Techniques for the addition of electrical connectors to current conveying fabrics are known. However, in the known techniques, continual wear and usage of the detector assembly often results in electrical connectors becoming disconnected from the material fabric, resulting in total system failure. It is therefore highly desirable to provide a system in which the electrical connector is held very securely to the material fabric itself so as to provide a robust system which does not become disconnected through continual use.

An improved approach to providing electrical connection to the electric current carrying conductors within the fabric is illustrated in Figure 18. Further modification is shown in Figure 19. In both of these systems, the fabric is constructed from electrically conducting fibres and from electrically insulating fibres by a mechanical process, such as weaving or knitting. An improved electrical connection is achieved by connecting electrical connection devices to the electrically conducting fibres of the fabric forming the detector during the mechanical fabric generating process. Thus, in the embodiments shown in Figure 18 and Figure 19, there is no requirement for adding connectors after a fabric has been created. The provision of a connector to the electric current carrying fibres is achieved during the actual mechanical process itself. Thus, for example, if the fibres are being produced by a knitting operation, part of this knitting operation involves procedures by which the electrical current carrying connector is actually included as part of the overall knit.

Fibres 1801 making up the weave are illustrated in Figure 18. A weaving procedure may be considered as generating woven fabric by traversing in the direction of arrow 1802. At pre-programmed positions, or at manually selected positions, modifications are made to the weaving process to the effect that a connector 1803 is to be introduced.

In the example shown in Figure 18, connector 1803 is an insulation displacement connector (IDC) allowing an insulated wire to be connected in such a way that it is not necessary to remove the insulation from the wire, given that the insulation is effectively cut as the wire, illustrated by reference 1804 is inserted into the connector in the direction of arrow 1805.

The weaving procedure is modified such that connector 1803 is included as part of the weave and is thereby held relatively firmly after the weaving procedure has been completed. In order to provide a further enhanced mechanical connection between electrical connector 1803 and the remaining woven fabric, additional layers of electrically conducting epoxy resin 1805 and 1806 are applied, such that, in operation, physical force applied to connector 1803 such that the connector will not, under normal circumstances, be displaced from the woven material of the device and will maintain electrical integrity.

A similar configuration is shown in Figure 19 in which a rivet fastener 1901 is applied during a weaving or knitting process, thereby substantially embedding the rivet fastener within the overall weave or knit. After the rivet fastener has been secured by the woven fabric 1902, electrically conducting epoxy resin 1903 is applied to provide enhanced mechanical and electrical stability.

In the configuration shown in Figure 1 and in the configuration shown in Figure 16, an electrical field is established over the transmitting plane. Given a plane of infinite size, the electrical field would have a regular geometric distribution and the position of a mechanical interaction could be determined from two voltage measurements in a substantially



straightforward way. However, in the configuration shown in Figure 1 and Figure 16, edges are present and these edges introduce severe distortions to the nature of the electric field from which measurements are being taken. In the control circuit 121 and within the data processing system 132 it is possible to provide a level of compensation, possibly in response to empirical measurements but such an approach has disadvantages, one of which being a loss of resolution.

Systems are shown in Figures 20 and 21 in which a detector is constructed from fabric having electrically conductive elements to define at least two electrically conducting planes. The detector is configured to produce an electrical output in response to a mechanical interaction. The relationship between mechanical interaction and electrical output is enhanced by introducing a conductivity non-uniformity which is included in at least one of the planes so as to modify an electrical response to the mechanical interaction.

In Figure 20, an electrical connector 2001 is connected to a plane at a first corner and a second connector 2002 is connected to the diagonally opposing corner. A configuration of this type could be used for a detector of the type shown in Figure 1, in which the electrical field effectively traverses across the diagonal corners, resulting in distortions at the edges. In the embodiment shown in Figure 20, a conducting thread 2003 with relatively low resistivity is included across edge 2004, electrically connected to connector 2001. Similarly, a second conducting thread 2005, with relatively low resistivity, extends from electrical connection 2002 along edge 2006. In this way, the whole of edge 2004 becomes conducting and the whole of edge 2006 becomes conducting. The resulting electric field is then substantially linear throughout the length of the detector thereby substantially eliminating non-linear edge effects.

In its co-operating plane 2010 a low resistance conducting thread 2011 is included along edge 2012 and a similar conducting thread is

provided along the opposing edge. In this way, the electric field traverses in a direction which is orthogonal to the electric field provided in the upper sheet, thereby allowing co-ordinates defined in mutually orthogonal co-ordinate space.

5           A conducting material is shown in Figure 21 in which areas 2101, close to all four edges, have had their conductivity modified, such that the overall conductivity of the sheet is non-uniform. This modification to conductivity may be achieved in several ways, including the addition of a  
10           conducting thread of the type illustrated in Figure 20. Alternatively, the modification to conductivity, to provide conductivity non-uniformity, may be achieved by a printing operation in which electrically conducting inks, possibly including silicon, are printed at region 2101. Alternatively, the density of conducting fibres in the woven material itself may be modified towards the edges of the detector, again resulting in a conductivity non-  
15           uniformity. Furthermore, it should be appreciated that modifications of this type may be achieved using combinations of the above identified effects in order to tailor the required level of non-uniformity for a particular application.

          In the configuration shown in Figure 1, a cycle is performed in which  
20           upper plane 102 effectively transmits allowing signals to be received by lower plane 103. A co-ordinate position is identified by reversing the operation of these planes, such that certain parts of the cycle include situations in which the lower plane 103 is effectively transmitting and the upper plane 102 is effectively transmitting. In a configuration of this type, it  
25           is preferable for the material types to be similar so as to provide substantially similar operations when plane 102 is transmitting or when plane 103 is transmitting. This is a particularly important constraint when the system is being used to measure current flow, given that different resistivities could be achieved in the different directions of current flow.

In the configuration shown in Figure 16, transmission always occurs from plane 1621, although in different orientations, and detection always occurs from plane 1622. With a configuration of this type, current always flows in the same direction therefore it is not essential for planes 1621 and 1622 to have equivalent mechanical constructions.

5

In the configuration shown in Figure 16, a detector is constructed from fabric having electrically conductive elements to define at least two electrically conductive planes and configured to produce an electrical output in response to a mechanical interaction. A second electrically conductive plane, such as plane 1622 of the detector, has at least one electrical characteristic that differs significantly in value from the value of said characteristic of the first plane 1621.

10

In the detector shown in Figure 16, the upper receiving plane 1622 has a significantly lower resistance than the lower transmitting plane 1621.

15

In this way, as the area of mechanical interaction increases, the amount of current flow increases significantly, thereby improving the definition of the system with respect to changes in the size of the mechanical interaction, and allowing for less intensive calculations when determining force etc.

## Claims

1. A detector constructed from fabric having electrically  
conductive elements to define at least two electrically conductive planes and  
configured to produce an electrical output in response to a mechanical  
interaction, wherein

a second electrically conductive plane of said detector has at least one  
electrical characteristic that differs significantly in value from the value of said  
characteristic of the first plane.

2. A detector according to claim 1, wherein one of said planes is  
used as a detector and voltages are applied sequentially in different  
directions to the other co-operating plane.

3. A detector according to claim 1 or claim 2, wherein said  
electrical characteristic is electrical resistance.

4. A position detector according to any of claims 1 to 3, wherein a  
second electrical property is determined to identify additional properties of  
said mechanical interactions.

5. A detector according to claim 4, configured to measure current  
or resistance at said second electrical property and configured to determine  
applied force, applied pressure, area of contact or orientation of an object as  
the additional property of said mechanical interactions.

6. A detector according to any of claims 1 to 5, wherein at least  
one of said planes includes first portions and second portions, said first  
portions having a higher resistance than said second portions and said first  
higher resistance portions being more flexible than said second portions.

7. A detector according to any of claims 1 to 6, wherein a detector surface is divided into a plurality of regions;

each of said regions includes a first conducting plane and a second  
5 conducting plane; and

a mechanical interaction results in conducting planes of at least one of said regions being brought closer together.

8. A detector according to any of claims 1 to 7, wherein said fabric  
10 has electrically conducting fibres and electrically insulating fibres, wherein electrical connection means are connected to said electrically conducting fibres of said fabric during a mechanical weaving or knitting process.

9. A detector according to any of claims 1 to 8, wherein a  
15 conductivity non-uniformity is included in at least one of said planes so as to modify an electrical response to a mechanical interaction.

10. A method of constructing a detector, comprising the steps of  
constructing electrically conductive elements from fabric to define at  
20 least two electrically conducting planes configured to produce electrical output in response to a mechanical interaction; and

configuring a second electrically conductive plane of said detector with at least one electrical characteristic that differs significantly in value from the value of said characteristic of said first plane.

25

11. A method of constructing a detector according to claim 10, wherein one of said planes is used as a detector and voltages are applied sequentially in different directions to the other co-operating plane.

12. A detector according to claim 10 or claim 11, wherein said electrical characteristic is electrical resistance.

5 13. A method according to any of claims 10 to 12, wherein a second electrical property is determined to identify additional properties of said mechanical interactions.

10 14. A method according to claim 13, wherein said detector is configured to measure current or resistance as said second electrical property and is configured to determine applied force, applied pressure, area of contact or orientation of an object as the additional property of said mechanical interactions.

15 15. A method according to any of claims 10 to 14, wherein at least one of said planes includes first portions and second portions, said first portions having a higher resistance than said second portions and said first higher resistance portions being more flexible than said second portions.

20 16. A method according to any of claims 10 to 15, wherein a detector surface is divided into a plurality of regions;

each of said regions includes a first conducting plane and a second conducting plane; and

a mechanical interaction resulting conducting planes of at least one of said regions being brought closer together.

25

30 17. A method according to any of claims 10 to 16, wherein said fabric has electrically conducting fibres and electrically insulating fibres, wherein electrical connection means are connected to said electrically conducting fibres of said fabric during a mechanical weaving or knitting process.

18. A method according to any of claims 10 to 17, wherein a conductivity non-uniformity is included in at least one of said planes so as to modify an electrical response to a mechanical interaction.



Application No: GB 9921925.5  
Claims searched: All

Examiner: Mark A Pullen  
Date of search: 20 January 2000

**Patents Act 1977**  
**Search Report under Section 17**

**Databases searched:**

UK Patent Office collections, including GB, EP, WO & US patent specifications, in:

UK CI (Ed.R): G1N (NACH, NACNR, NAEPR, NAGB8, NAGB10, NAGBR, NAQB),  
H1N (NUJD)

Int CI (Ed.7): G01L 1/20, G06K 11/12

Other: ONLINE : WPI, EPODOC, JAPIO

**Documents considered to be relevant:**

Category	Identity of document and relevant passage	Relevant to claims
A	GB 1308575 (DATA APPLIANCES CORP)	

- |   |                                                                                                           |   |                                                                                                                  |
|---|-----------------------------------------------------------------------------------------------------------|---|------------------------------------------------------------------------------------------------------------------|
| X | Document indicating lack of novelty or inventive step                                                     | A | Document indicating technological background and/or state of the art                                             |
| Y | Document indicating lack of inventive step if combined with one or more other documents of same category. | P | Document published on or after the declared priority date but before the filing date of this invention.          |
| & | Member of the same patent family                                                                          | E | Patent document published on or after, but with priority date earlier than, the filing date of this application. |



**This Page is Inserted by IFW Indexing and Scanning  
Operations and is not part of the Official Record**

## **BEST AVAILABLE IMAGES**

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** \_\_\_\_\_

**IMAGES ARE BEST AVAILABLE COPY.**

**As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.**